

8080 Microcomputer

	A	C		I/O Port Numbers	
1	GND	1	GND	60-6E	Parallel Ports
2	+5v	2	+5v	70-7F	DMA Controller
3	-12v	3	+12v	80-8F	Serial Ports
4	DMARDY	4	~EOT	90-93	8253 Timer
5	A0	5	~MEMR	FE	8214 Interrupt Status
6	A1	6	~MEMW	FF	Bank Switch
7	A2	7	~I/OR		
8	A3	8	~I/OW		
9	A4	9	HOLD		
10	A5	10	HLDA		
11	A6	11	INT		
12	A7	12	INTE		
13	A8	13	READY		
14	A9	14	WAIT		
15	A10	15	~RES		
16	A11	16	~IRQ7		
17	A12	17	~IRQ6		
18	A13	18	~IRQ5		
19	A14	19	~IRQ4		
20	A15	20	~IRQ3	IRQ 0	8253 Timer
21	D0	21	~IRQ2	IRQ 1	Serial Port RxREADY
22	D1	22	~IRQ1	IRQ 2	
23	D2	23	~IRQ0	IRQ 3	
24	D3	24	~DMA1	IRQ 4	
25	D4	25	~DACK1	IRQ 5	
26	D5	26	~DMA2	IRQ 6	
27	D6	27	~DACK2	IRQ 7	
28	D7	28	~DMA3		
29	SYNC	29	~DACK3		
30	CLK	30	INTA		
31	+5v	31	+5v		
32	GND	32	GND		